



Wiring Diagram

Microtran Audio Transformer **(TA) M7418**

TA-M7418 Pin-out

Primary:

- Terminals 1 and 3 are the 1K ohm winding with terminal 2 as the center tap.
- Terminals 1 and 4 are the 2K ohm winding with terminal 3 as the center tap.
- Terminals 1 and 5 are the 4K ohm winding with terminal 4 as the center tap.
- Terminals 1 and 6 are the 8K ohm winding with terminal 5 as the center tap.
- Terminals 1 and 7 are the 32K ohm winding. There is no center tap of the 32K ohm winding.

Secondary:

- Terminals 8 and 11 are the 0.5 ohm winding.
- Terminals 9 and 11 are the 2 ohm winding.
- Terminals 10 and 11 are the 8 ohm winding.